

MANUALE **CONNESIONE DISPOSITIVO AL CLOUD**

MANUALE OPERATIVO Display LED Fullcolor

Impostazioni per la connessione del dispositivo al Cloud

1. Creare un account accedendo all'indirizzo web: <u>http://www.led-cloud.com</u>

	Quick Sign-in						
Us	Username / Email						
Pa	issword						
	Sign In						
	Forgot password? Sign Up						
	Sign Up						
Username:							
Password :							
Confirm password :							
Company :							
Phone :							
Email :	Sand Cada						
venication code .	By clicking on "Sign up now" below, you are agreeing to the Privacy Policy.						
	Sign up pow						
	Cign up non						

Nota: il numero di telefono "Phone" non è un campo richiesto per la creazione dell'account.

2. Collegare il dispositivo al PC attraverso il cavo di rete. Utilizzare il programma *HDPlayer* per impostare il dispositivo: configurare le impostazioni dello schermo e le impostazioni hardware per la corretta visualizzazione dei contenuti sullo schermo del dispositivo.





👌 Clou	id Server					×
	Device ID	Device name	Server/Port	Server/Port Username		_
	D30-99-A0000	BoxPlayer	www.led-cloud.com	×	Tech_Display	×
	D30-99-A0001	BoxPlayer	www.led-cloud.com	×	Tech_Display	×
	D30-99-A0005	BoxPlayer	www.led-cloud.com	×	Tech_Display	×
	D30-99-A0003	BoxPlayer	www.led-cloud.com	×	Tech_Display	×
	C30-00-C0729	BoxPlayer	www.led-cloud.com	×	Tech_Display	×
	C30-00-B5100	BoxPlayer	www.led-cloud.com	×	Tech_Display	×
	D10-00-A0810	BoxPlayer	www.led-cloud.com	×	Tech_Display	×
	C30-00-C0730	BoxPlayer	www.led-cloud.com	×	Tech_Display	×
	D30-99-A0004	BoxPlayer	www.led-cloud.com	×	Tech_Display	×
	C30-00-A9717	BoxPlayer	www.led-cloud.com	×	Tech_Display	×
C					ОК	Cancel

3. Collegare il dispositivo a internet attraverso il cavo di rete connesso al router, quindi spegnere e riaccendere il dispositivo. Sarà ora nello stato online in <u>http://www.led-cloud.com</u> (Se utilizzi il 3G / 4G, inserisci la scheda SIM e rimuovi il cavo di rete).

🔒 Devices List	Device Info Device ID : Device Name : Search Refresh									
Unaudited Device		Device ID	Device Name	Resolution	Firmware	Update Time	Branch n	Online	Options	
		A30-15-A4897	HD Display	160x128	5.3.99.0	2017-11-13 14:59:19		(0)	> Details	*

Quando il dispositivo è online, questo sarà categorizzato come "Unaudited Device", Quando verrà verificato dal gestore del server Huidu, cambierà la categoria in "Devices list".

IIII LED Display Cl	oud Platfo	orm	Devi	c e Proç					
Devices List	Device	> Info	Devi	ice Name :		Search	Refresh D	elete	
Unaudited Device O Time Correction Brightness settings Switch settings Set Heartbeat Plot Upgrade Firmware Key Definitions									
		Device ID	Device Name	Resolution	Firmware	Update Time	Branch n	Online	Options
		A30-15-A4897	HD Display	160x128	5.3.99.0	2017-11-13 14:59:19		(03)	> Details ^

- 4. Se il dispositivo non risulta online, controlla quanto segue:
 - 1) Controlla che "server/port" e "username" siano stati inseriti correttamente nella voce "cloud server" in HDPlayer.
 - 2) Controlla che che il router sia connesso alla rete internet.
 - 3) Accedi al programma HDPlayer. Collega il dispositivo al PC con il cavo di rete, quindi fare clic 💿 su "Device information", controlla il 3G / 4G.

👌 HDPlayer					
File Setting	<u>Control</u> anguage Help				
💽 Program	📰 Device Information 💊 🗴 🍱 Photo 📑 1				
Send	Exporting to U-disk Cluster Sending				
	 Brightness Setting Time Correction 				
A 💽 PROGR	Time Switch				
	Update Device Name				
	Screen Testing				
	Other setting				
Device Information					
Select device:	A601-1606-A0984 A601+4G • 🗸 🖒				
Device Information	Vifi				
Device Information	Module Not accessed				
Brightness setting 3G / 4G network					
ime coffection	Module EC20				
Switch machine settings Network settings	cellphone number				

network status

Key function

Brightness sensor

Temperature Sensor

Humidity Sensor

GPS +

other information

LTE-FDD

Screen Testing

Not accessed

Not accessed

Not accessed

Not accessed

.

att

Edit

S Device Information		×
Select device:	A601-1606-A0984	A601+4G 🔹 🗸
Device Information	APN	
		APN 3gnet 💉 🚺
Brightness setting	Mobile numb	.ber:
Time correction	RS	:SSI: −24dBm
Switch machine settings	Operat	itor: CHN-UNICOM
Network settings	Ro	loam: Non-roaming
3G / 4G settings	Netwo	ork: LTE-FDD
startup screen	Stat	utus: Register
Trial authorization	Manufactur	wer: Questel EC20
	אנו	MEI: 868323021801698
	Versi	ion: EC20CQDR02A03E2G
	<	Ok Cancel

Nota: per alcune schede SIM è necessario impostare l'APN. Per questa informazione è possibile contattare il proprio gestore telefonico.

- • • •
- • • •
-
- • • •
- • • •
- • • •
- • • •
- • • •
- • • •
- • • •
- ••••
- • • •
- • • •
-
- • • •
- • • •
- • • •
- • • •



Via Novara, 21 - 28019 Suno (NO) - Italy Telefono: +39 0322 858688 Email: info@techsrl.it www.techsrl.it